

LifeSmart

BLEND Switch

Single Live

User Guide V1.0


Model: LS240 Single Live series

INSTRUCTION



The Single Live series of LifeSmart BLEND Switch PRO and BLEND Switch PRO Metal replaces your traditional switch with smart home technology to make your life easier. Combined with the LifeSmart Smart Station and the free LifeSmart App, you have infinite control possibilities.

The Single Live series switch adopts extremely low power consumption technology, works independently without an external power. It supports single live line, null and live line and low direct current, and also can be used as passive switch. It eliminates the flicker when a traditional single live line switch is connected to a low power light bulb, providing an easy solution for installation and use.

SPECIFICATIONS

Size	Outside the wall: 86*86*11mm Overall: 86*86*36mm
Weight	PRO: 116g(1way) 128g(2 way) 140g(3 way) Metal: 131g(1way) 143g(2 way) 155g(3 way)
Power consumption	<1mW
Input	AC 90-250V~50/60Hz or DC 5-30V 
Maximum load	Resistive Load: 500W per channel Inductive/Capacitive Load: 200W per channel
Wireless protocol	CoSS
Wireless distance	200m(open field)
Operating temperature	-5~45°C
Operating humidity	5~90%
Battery type	CR123A DC3V
Standby duration	Up to 5 years

WIRING INSTRUCTION



Lin: Switch-in Live Wire L1/L2/L3: Switch-out Live Wire for each way

NOTE:

The number of output lines varies according to different smart control accessories, please refer to the actual product.

It is recommended that the installation height does not exceed 2 meters. The installation involves high voltage and should be done by a professional electrician.

The panel and accessory of the product must be used together. Do not disassemble and use them for other products.

Please refer to the actual product appearance.

INSTALLATION

- ① Cut off the electrical power supply and make sure the wiring is not charged.
- ② Take out the smart control accessory and install it according to the wiring instruction, make sure **all** the wires are placed firmly.
- ③ Place the wires in the cassette orderly, and fix the smart control accessory to the cassette with fixing screws.
- ④ Remove the package of the battery and place it into the battery box.
- ⑤ Take out the switch panel and fix it to smart control accessory, make sure that the upper and lower two buckles are in place, otherwise it may not be able to be used normally due to poor contact. Then restore the power supply.
- ⑥ After configuration of the Smart Station, choose “**Add Device**” in LifeSmart App, select “**BLEND Switch PRO**” or “**BLEND Switch PRO Metal**” to enter pairing process. Follow the instruction on the app to finish pairing.

WARRANTY DESCRIPTION

Thank you for purchasing this LifeSmart product. In order to protect your rights, please read the following content carefully: The warranty period of our company's products is one year from the date of purchase or longer if local laws impose a longer minimum term, in which case the minimum term is the warranty period. During the warranty period, any faults caused by the product itself or for quality problems that arise under normal usage, LifeSmart will provide a free replacement.

User support e-mail address

support@ilifsmart.com

Website

iot.ilifsmart.com



Manufacturer: HANGZHOU LIFESMART TECHNOLOGY CO.,LTD.

Address: 22th Floor, Yuesheng International Center, 518 Pinglan Road, Xiaoshan District, Hangzhou, Zhejiang, China

ATTENTION

The following conditions are not covered by the warranty:

- Product failure or damage caused by installation, use, and maintenance that is not in accordance with the product instructions;
- Products beyond the warranty period;
- Products that have the barcode tampered with or removed;
- Devices that have been tampered with or customized outside of LifeSmart Terms Of Service as on the LifeSmart APP and website;
- User-caused damage, such as inappropriate voltage input, high temperature, accidental spillage, physical damage, etc;
- Product failure or damage caused by force majeure such as earthquakes, fires, or floods;
- Product failure or damage caused by other problems except the product itself.

DECLARATION

DECLARATION OF CONFORMITY

Hereby, LifeSmart declares that the radio equipment type is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following internet address:

<http://global.ilifsmart.com/ce/docs/>



Notice: This device may be used in each member state in EU.

DISPOSAL AND RECYCLE INFORMATION

Device labelled with this symbol should not be disposed with other household wastes. It shall be handed over to the applicable collection point for the recycling of waste electrical and electronic equipment.



 Facebook: ilifsmarthome

 Twitter: ilifsmarthome

Copyright © 2022 LifeSmart Inc. All Rights Reserved.