

LifeSmart

Nature Switch

User Guide V1.0

Model: LS220 Nature Switch (Scene Panel) series

INSTRUCTION

LifeSmart's Nature Switch (Scene Panel) adopts Touch Pro technology and brings ultimate touch experience for lighting. It is also designed with DIY colorful LED indicator, you can turn on the light easily in the dark. The cover adopts tempered glass with oleophobic coating, which is wear resistant and easy for cleaning & maintenance.

Nature Switch (Scene Panel) supports two-way communication and mobile control. You can manage it through our App whenever and wherever. It can be paired with other smart devices to trigger Smart Scenes like light on when you come home and lights out when you leave the house.

SPECIFICATIONS

Size	Outside the wall: 86*86*11mm Overall: 86*86*36mm
Weight	126g(1way) 138g(2 way) 150g(3 way) 114g(without relay)
Power consumption	<0.6W
Input	AC 100-240V~ 50/60Hz
Maximum load	Resistive Load: 500W per channel Inductive/Capacitive Load: 200W per channel
Wireless protocol	CoSS
Wireless distance	200m(open field)
Operating temperature	-5~45°C
Operating humidity	5~90%

WIRING INSTRUCTION


L3: Switch-out Live Wire 3

L2: Switch-out Live Wire 2

L1: Switch-out Live Wire 1


L: Switch-in Live Wire

N: Switch-in Neutral Wire



NOTE: The number of output lines varies according to different smart control accessories, please refer to the actual product. It is recommended that the installation height does not exceed 2 meters.

WARNING: The installation involves high voltage and should be done by a professional electrician.



INSTALLATION

- ① Cut off the electrical power supply and make sure the wiring is not charged.
- ② Take out the smart control accessory and install it according to the wiring instruction, make sure all the wires are placed firmly.
- ③ Place the wires in the cassette orderly, and fix the smart control accessory to the cassette with fixing screws.
- ④ Take out the switch panel and fix it to smart control accessory, make sure that the upper and lower two buckles are in place, otherwise it may not be able to be used normally due to poor contact.
- ⑤ Restore the power supply, the device will turn on automatically.
- ⑥ After configuration of the Smart Station, choose “**Add Device**” in LifeSmart App, select “**Nature Switch**” or “**Nature Switch Scene Panel**” to enter pairing process. Follow the instruction on the app to finish pairing.

WARRANTY DESCRIPTION

Thank you for purchasing this LifeSmart product. In order to protect your rights, please read the following content carefully: The warranty period of our company's products is one year from the date of purchase or longer if local laws impose a longer minimum term, in which case the minimum term is the warranty period. During the warranty period, any faults caused by the product itself or for quality problems that arise under normal usage, LifeSmart will provide a free replacement.

User support e-mail address

support@ilifsmart.com

Website

iot.ilifsmart.com



Manufacturer: HANGZHOU LIFESMART TECHNOLOGY CO.,LTD.

Address: 22th Floor, Yuesheng International Center, 518 Pinglan Road, Xiaoshan District, Hangzhou, Zhejiang, China

ATTENTION

The following conditions are not covered by the warranty:

- Product failure or damage caused by installation, use, and maintenance that is not in accordance with the product instructions;
- Products beyond the warranty period;
- Products that have the barcode tampered with or removed;
- Devices that have been tampered with or customized outside of LifeSmart Terms Of Service as on the LifeSmart APP and website;
- User-caused damage, such as inappropriate voltage input, high temperature, accidental spillage, physical damage, etc;
- Product failure or damage caused by force majeure such as earthquakes, fires, or floods;
- Product failure or damage caused by other problems except the product itself.

DECLARATION

DECLARATION OF CONFORMITY

Hereby, LifeSmart declares that the radio equipment type is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following internet address:

<http://global.ilifsmart.com/ce/docs/>



Notice: This device may be used in each member state in EU.

DISPOSAL AND RECYCLE INFORMATION

Device labelled with this symbol should not be disposed with other household wastes. It shall be handed over to the applicable collection point for the recycling of waste electrical and electronic equipment.



 Facebook: ilifsmarthome

 Twitter: ilifsmarthome

Copyright © 2021 LifeSmart Inc. All Rights Reserved.