

LifeSmart

BLEND Switch

User Guide V1.0

Model: LS230,LS240 series

INSTRUCTION

The LifeSmart BLEND Switch Series replaces your traditional switch with smart home technology to make your life easier.

Combined with the LifeSmart Smart Station and the free LifeSmart App, you have infinite control possibilities.



In addition to traditional switch control of your lights and switched outlets, you can choose combination controls over all of your LifeSmart Smart Home products.

The decorative LED lights on LifeSmart BLEND Switch are customizable via the mobile app, which makes it easier to turn on or off lights in the dark.

SPECIFICATIONS

Size	Outside the wall: 86*86*11mm Overall: 86*86*36mm
Weight	PRO: 124g(1way) 136g(2 way) 148g(3 way) Lite: 121g(1way) 129g(2 way) 137g(3 way)
Power consumption	PRO: <0.6W Lite: <1.5W
Input	AC 100-240V 50/60Hz
Maximum load	Resistive Load: 500W per channel Inductive/Capacitive Load: 200W per channel
Wireless protocol	CoSS
Wireless distance	200m(open field)
Operating temperature	-5~45°C
Operating humidity	5~90%

WIRING INSTRUCTION



L3: Switch-out Live Wire 3

L: Switch-in Live Wire

L2: Switch-out Live Wire 2

N: Switch-in Neutral Wire

L1: Switch-out Live Wire 1

NOTE:

The number of output lines varies according to different smart control accessories, please refer to the actual product.

It is recommended that the installation height does not exceed 2 meters. The installation involves high voltage and should be done by a professional electrician.

Please refer to the actual product appearance.

INSTALLATION

- ① Cut off the electrical power supply and make sure the wiring is not charged.
- ② Take out the smart control accessory and install it according to the wiring instruction, make sure all the wires are placed firmly.
- ③ Place the wires in the cassette orderly, and fix the smart control accessory to the cassette with fixing screws.
- ④ Take out the switch panel and fix it to smart control accessory, make sure that the upper and lower two buckles are in place, otherwise it may not be able to be used normally due to poor contact.
- ⑤ Restore the power supply, the device will turn on automatically.
- ⑥ After configuration of the Smart Station, choose “Add Device” in LifeSmart App, select “BLEND Switch PRO” or “BLEND Switch Lite” to enter pairing process. Follow the instruction on the app to finish pairing.

WARRANTY DESCRIPTION

Thank you for purchasing this LifeSmart product. In order to protect your rights, please read the following content carefully: The warranty period of our company's products is one year from the date of purchase or longer if local laws impose a longer minimum term, in which case the minimum term is the warranty period. During the warranty period, any faults caused by the product itself or for quality problems that arise under normal usage, LifeSmart will provide a free replacement.

User support e-mail address

support@ilifsmart.com

Website

iot.ilifsmart.com



Manufacturer: HANGZHOU LIFESMART TECHNOLOGY CO.,LTD.

Address: 22th Floor, Yuesheng International Center, 518 Pinglan Road, Xiaoshan District, Hangzhou, Zhejiang, China

ATTENTION

The following conditions are not covered by the warranty:

- Product failure or damage caused by installation, use, and maintenance that is not in accordance with the product instructions;
- Products beyond the warranty period;
- Products that have the barcode tampered with or removed;
- Devices that have been tampered with or customized outside of LifeSmart Terms Of Service as on the LifeSmart APP and website;
- User-caused damage, such as inappropriate voltage input, high temperature, accidental spillage, physical damage, etc;
- Product failure or damage caused by force majeure such as earthquakes, fires, or floods;
- Product failure or damage caused by other problems except the product itself.

DECLARATION

DECLARATION OF CONFORMITY

Hereby, LifeSmart declares that the radio equipment type is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following internet address:

<http://global.ilifsmart.com/ce/docs/>



Notice: This device may be used in each member state in EU.

DISPOSAL AND RECYCLE INFORMATION

Device labelled with this symbol should not be disposed with other household wastes. It shall be handed over to the applicable collection point for the recycling of waste electrical and electronic equipment.



 Facebook: ilifsmarthome

 Twitter: ilifsmarthome

Copyright © 2022 LifeSmart Inc. All Rights Reserved.